

PART NUMBER <h1 style="margin: 0;">KAD177013</h1>	<table border="1" style="width: 100%; border-collapse: collapse;"> <tr> <th style="width: 10%;">REV.</th> <th style="width: 10%;">DATE</th> <th style="width: 40%;">COMMENTS</th> <th style="width: 40%;">INITIAL</th> </tr> <tr> <td> </td> <td> </td> <td> </td> <td> </td> </tr> </table> <div style="text-align: right; font-weight: bold; margin-top: 10px;">RoHS Compliant</div> <div style="margin-top: 20px;"> Electrical Data <div style="display: flex; justify-content: space-between; margin-top: 10px;"> Impedance 50 Ω </div> </div> <div style="text-align: center; margin-top: 40px;"> <p>Technical drawing of the KAD177013 adapter. The side view shows a central threaded section with a hex nut and washer. Dimensions include: total length 0.937 (23.8), SMA section length 0.449 (11.4), SMA outer diameter Ø 0.394 (10), hex size 0.315 (8.0), and thread 1/4-36UNS-2B. The top view shows a circular SMA connector with a recommended mounting hole diameter of Ø 0.252 (6.4) and a hole diameter of 0.236 (6.0).</p> </div> <div style="margin-top: 20px; font-size: small;"> Drawing not to scale. Dimensions for reference only Units: inches (mm) </div>	REV.	DATE	COMMENTS	INITIAL				
REV.	DATE	COMMENTS	INITIAL						

Konnekt RF

WWW.KONNECTRF.COM

1-800-790-5887

PART NUMBER <h1 style="margin: 0;">KAD177013</h1>		DESCRIPTION Adapter, Between Series, SMA Female Jack to MMCX Female Jack Bulkhead Mount													
CAGE CODE <h1 style="margin: 0;">664U0</h1>	SIGNATURE <div style="text-align: center; margin-top: 10px;"> </div>	<table style="width: 100%; border-collapse: collapse;"> <tr> <th style="width: 33%; text-align: left;">Component</th> <th style="width: 33%; text-align: left;">Material</th> <th style="width: 33%; text-align: left;">Plating</th> </tr> <tr> <td>Body, Nut, & Washer</td> <td>Brass</td> <td>Gold</td> </tr> <tr> <td>Center Contact</td> <td>BeCu</td> <td>Gold</td> </tr> <tr> <td>Insulator</td> <td>PTFE</td> <td> </td> </tr> </table>		Component	Material	Plating	Body, Nut, & Washer	Brass	Gold	Center Contact	BeCu	Gold	Insulator	PTFE	
Component	Material	Plating													
Body, Nut, & Washer	Brass	Gold													
Center Contact	BeCu	Gold													
Insulator	PTFE														
THIS DRAWING INCLUDING THE DESIGNS IS THE PROPERTY OF KONNECT RF AND IS NOT TO BE USED FOR ANY PURPOSE WITHOUT OUR APPROVAL.		<div> </div>													