PART NUMBER

KIMP177301


REV.	DATE	COMMENTS	INITIAL

RoHS Compliant

Electrical Data

Impedance 50 Ω (BNC Female Side) 75 Ω (F Male Side)

Insertion Loss 5.7 dB
Frequency Range DC-2 Ghz
VSWR 1.40 Max
Input Power 1 Watt average







Drawing not to scale. Dimensions for reference only

Units: Inches

H Konnect RF

WWW.KONNECTRF.COM 1-800-790-5887

PART NUMBER KIMI	P17730/1	Impedance Matching Pad, 50 Ohm BNC Female Jack to 75 Ohm F Male Plug	
CAGE CODE	SIGNATURE //		
664U0	<u>x</u> ///		
THIS DRAWIN	IG INCLUDING THE]	
DESIGNS IS T	HE PROPERTY OF		
KONNECT RF	AND IS NOT TO		
BE USED FOR	R ANY PURPOSE		
WITHOUT OU	R APPROVAL.		
1		I	